



2N[®]

SIM Star Server



How to activate SIM on SIM Star Server

Quick guide

Version 1.00

www.2n.cz

2N® SIM Star Server - How to activate SIM

Before you begin reading this guide, you will need following settings/equipment already prepared:

- *fully operational gateway and SIM Star Server*
- *one GSM Group, one SIM Group and one Rule created at least*
- *SIM cards assigned to SIM Group, properly set credit checking procedure (if prepaid SIMs used)*

1) GSM Group

Check settings of GSM Group which will be used for activation, it has to be unrestricted for activation. Regarding your requests please select one of following restriction options:

- **No restriction**
- **Use SIM cards with recharging or activation request only**
- **Use SIM cards with activation request only**

Edit GSM group 1

General info

Description: T-Mobile GSM Group

Highlighting: [Color palette] # FF 60 FF

Gateway routing

Outgoing group: Default ?

Incomming group: Default ?

Recharging and activation

Restriction: No restriction ?

BTS lock

BTS lock type: ?

Min. signal level:

1. GSM/UMTS ID: 23001 Used BTS:

2) SIM Group

Edit SIM group which will be used for activation and go to the **1st SIM card activation settings** section. Till SIM Star Server **version 1.7.0 are 2 activations** available, from **version 1.8.0 are up to 6 activations** available.

Here set up following settings (marked **bold** is necessary):

- **Type** – USSD, SMS or IVR – choose **one** of recharging possibilities

- **Number(s)** – if you use type SMS or IVR, enter here number(s) for send/dial. You can define more phone numbers separated by semicolons for random choose.

The screenshot displays a configuration interface for SIM card activation settings. It is organized into six sections, each for a different SIM card (1st to 6th). The first section, '1st SIM card activation settings', is expanded to show various parameters:

- Type:** A dropdown menu set to 'USSD'.
- Number(s):** A text input field, currently empty.
- String:** A text input field containing '*101#'.
- Act. idle time (min):** A numeric input field set to '0', with a range of '(0 - 10000)'.
- Activate new SIMs:** A checked checkbox.
- Act. recharged SIMs:** An unchecked checkbox.
- Activation day:** A dropdown menu set to 'Never'.
- Minimal credit:** A numeric input field set to '0' with a decimal part set to '00', and a range of '(0 - 10000 / 0 - 99)'.
- Keep logged after act.:** An unchecked checkbox.

The remaining sections for the 2nd, 3rd, 4th, 5th, and 6th SIM cards are collapsed, each showing only the section header and a small expand/collapse icon.

- **String:**
 - o **USSD** – code to send (for ex. *101#). For USSD menu browsing use the semicolon as a delimiter of steps.
 - o **SMS** – text of recharging SMS (for ex. ACTIVATE %n – send SMS with text ACTIVATE assign phone number of SIM)
 - o **IVR** – sequence of tones and delays (ex. pP1w9W – wait 1+2 seconds, press 1, wait 5 seconds, press 9, wait 10 seconds)
 - p – pause 1 second
 - P – pause 2 seconds
 - w – pause 5 seconds
 - W – pause 10 seconds
 - *#0123456789 – DTMF codes
- Act. idle time (min) – after successful activation this time is used instead of idle time
- Activate new SIMs – activation for new inserted SIM cards will be requested
- Act. recharged SIMs – activation for recharged SIM cards will be requested
- Activation day – you can specify day when SIM cards are automatically activated
- Minimal credit – minimal credit balance of SIM card before activation

- Keep logged after act. – keep SIM card logged after successful activation (otherwise SIM is logged out before next use)

3) Activate SIM

a) Activate new SIMs in SIM Group settings enabled

All new SIM cards added to the specific SIM Group are automatically activated.

b) Activation day (auto activation) in SIM Group settings enabled

All SIM cards in the specific SIM Group are automatically activated on selected day (for ex. every x-th day of month/week etc.).

c) Activate SIM manually

Go to: **SIMs** – choose specific SIM and click on edit  icon on the row

Show SIM board: All SIM boards | Show disabled: all

Show SIM group: All SIMs (grouped and ungrouped) | Show blocked: all

Show positions: All SIMs (used and unused) | Show SIM types: all

Table menu, Action menu, SIM channels on SIM Board

SIM board [1] New Sim board

IMSI	Ch.	Group	Status	Assigned to	Hard linked	IMEI	Type	Remark	Disabled	Blocked						
230020700988089	0	[G]	Ok	gw 0 ch 7	gw 0 ch 7	no	tariff		no	no	→	✏	✖	⌵	☐	
230022901132085	1	[G]	Ok			no	tariff		no	no	→	✏	✖	⌵	☐	
214074200000566	2	[G]	Ok			no	tariff		no	no	→	✏	✖	⌵	☐	
	3		[None]													
214074200002014	4	[G]	Ok			no	tariff	O2 Spain M2M testing SIM	no	no	→	✏	✖	⌵	☐	
214074200000566	5	[G]	Ok			no	tariff	O2 Spain M2M testing SIM	no	no	→	✏	✖	⌵	☐	
	6		[None]													
	7		[PIN - blocked]													
	8		[None]													

When editing SIM you can select activation(s) you would like to proceed (up to 2 or 6 activations depending on the SIM Star Server version).

Edit SIM 214074200000566

General info

SIM group: [1] T-Mobile SIM Group

SIM type: tariff

Remark:


Phone number: ?

Disabled:

Unblock

<input type="checkbox"/> Request 1st activation	<input type="checkbox"/> Cancel 1st activation
<input type="checkbox"/> Request 2nd activation	<input type="checkbox"/> Cancel 2nd activation
<input type="checkbox"/> Request 3rd activation	<input type="checkbox"/> Cancel 3rd activation
<input type="checkbox"/> Request 4th activation	<input type="checkbox"/> Cancel 4th activation
<input type="checkbox"/> Request 5th activation	<input type="checkbox"/> Cancel 5th activation
<input type="checkbox"/> Request 6th activation	<input type="checkbox"/> Cancel 6th activation

4) Activation result

When activation proceeded you will see the result in the detail clicking on the View  button on the row of specific SIM.

General info

View SIM 230020700966089

[Back to SIMs](#), [Edit](#), [Remove](#), [Action menu](#), [ASR graph](#), [ACD graph](#)

General info

SIM board: [\[1\] New Sim board](#)
Channel: 0
SIM group: [\[1\] T-Mobile SIM Group](#)
SIM type: tariff
Remark:
Phone number: 728594661
SCID: 8942020399605158317
Disabled: no
Blocked: no

Blocked count

Failed calls: 0
Short calls: 0
Failed SMSs: 0
Failed logins: 0
Failed credit checks: 0
Failed rechargings: 0
Registration error: 0
Incorrect plan: 0

Tariff SIM card info

Free minutes: 0
Actual free minutes: 0
Free SMSs: used from SIM group
Actual free SMSs: 0

Tariff SIM card - call tariffs info

	Tariff 1	Tariff 2	Tariff 3	Tariff 4
Actual free minutes:	0	0	0	0

Prepaid SIM card info

Actual credit: 0.00
Actual rech. count: 0

Assigned IMEI

No IMEI assigned

ASR (Answer Seizure Ratio)

Total SIM usage: no calls
Last SIM usage: no calls

ACD (Average Call Duration)

Total SIM usage: no calls
Last SIM usage: no calls

Activation USSD answers

1st: ok
2nd:
3rd: MSISDN:j673790876
4th:
5th:
6th:

SIM status info

Status: **Ok**
Assigned to: [gw 0 ch 7 \(id: 7\)](#)
Hard linked to: [gw 0 ch 7 \(id: 7\)](#)
Last used in: [gw 0 ch 7 \(id: 7\)](#)
Last login: 2012/07/27 - 08:35:48 dst (Server local time)
Last logout: 2012/07/27 - 08:35:47 dst (Server local time)
Time using: 0d 21h 16m
Total time using: 0d 21h 16m

Last gateways

[0] (2012/07/27 - 08:33:14 dst / 2012/07/27 - 08:35:47 dst)
[0] (2012/07/26 - 11:15:19 dst / 2012/07/27 - 08:33:12 dst)
[1] (2012/06/16 - 15:15:40 dst / 2012/06/16 - 15:17:17 dst)
[1] (2012/06/16 - 15:13:58 dst / 2012/06/16 - 15:15:37 dst)
[1] (2012/06/16 - 15:12:18 dst / 2012/06/16 - 15:13:57 dst)

Active recharging

none

Activation status

1st: Activated, 2012/07/18 - 06:07:59 dst
2nd: Not requested
3rd: Activated, 2012/06/21 - 15:15:15 dst
4th: Not requested
5th: Not requested
6th: Not requested

Lookup info

Already used